


Quick Installation Guide  

TV-H400
2.11

Table of Contents

English	1
1. Before You Start	1
2. Hardware Installation	2
Troubleshooting	11



Package Contents

- TV-H400
- Quick Installation Guide
- Power Adapter (12V DC, 0.6A)
- 1 x Wall Mount Bracket
- Allen wrench (4mm)
- Screws and lock washers
- Rubber seal


System Requirements

The following items below are not included. Users must provide the items themselves. Make sure to have each item on hand before installation.


- Pan and tilt Internet camera
- Mounting screws and screw anchors (for wall mounting)
- Dry wall or wood surface
- Phillips screwdriver
- RJ-45 Ethernet cable

2. Hardware Installation


Note: Configure your Internet Camera Server to match your network before installing the device.



1. Rotate the TV-H400's cover counter clockwise and remove the cover.



2. Unscrew the thumbscrew. Save this screw. You will need to use this screw later.




3. Run all necessary cables (Ethernet cable, power adapter cable, and the power terminals) through the wall mount bracket.




4. Connect the power terminal to the provided 12V DC, 0.6A power adapter.



5. Run each cable through the opening located at the top of the TV-H400.



6. After inserting the appropriate cables, extend each cable to 6 inches for camera installation.




7. Use the provided rubber seal to seal the housing.




8. Secure the protective plating into the wall mount bracket using the thumb screw.



9. Screw the wall mount bracket on top of the TV-H400 with the provided Allen wrench and three hexagon socket screws. The screws are in the plastic bag labeled Q2.



10. Connect the three 5 cm Hex screws to the circular base bracket. Secure the Hex screws with the nuts and washers. The 5cm Hex screws are in the plastic bag labeled Q3. The nuts and washers are in the plastic bag labeled Q5.



11. Mount bracket **BR003** to the camera enclosure using the three flat head screws. These screws are in the plastic bag labeled **Q1**.




12. Use three round head screws to mount bracket **BR002** on top of the 3 Hex screws. The three round head screws are in the plastic bag labeled **Q6**.



13. Connect the two 3 cm hex screws to this bracket. These screws are in the plastic bag labeled **Q4**.



14. Attach bracket **BR001** to the camera with 3 small screws. These screws should come with the Internet Camera Server.



15. Use the two round head screws to mount bracket **BR001** to the two hex screws. The two round head screws are in the plastic bag labeled **Q6**.



16. Connect the Ethernet cable and power adapter to the Internet Camera Server.



- 17.** Place the TV-H400's cover over the camera and rotate the cover clock-wise.



- 18.** Plug the power to the Internet Camera Server and the camera enclosure into an available power outlet.

Mounting the Camera Enclosure


Note: Mounting screws and screw anchors are not included.

1. Place the mounting bracket against the wall or ceiling and mark each of the four holes with a pencil.




2. Drill holes for the screws at each marked position.

3. Insert screw anchors into the holes.



4. Align the wall mount bracket with the screws, and then use nuts and washers to secure it.



Your Installation is complete

For detailed information regarding the **TV-H400** configuration and advanced settings, please visit TRENDnet's website at www.trendnet.com

Register Your Product

To ensure the highest level of customer service and support, please take a moment to register your product Online at: www.trendnet.com/register

Thank you for choosing TRENDnet

After I put my Internet Camera Server in the enclosure, the image is distorted. What should I do?

1. Make sure that you have adjusted the focus on your camera.
2. Mount the TV-H400, so that it's not in direct view of the sun.

Does the TV-IP422 and TV-IP422W work with the TV-H400?

We do not recommend using the TV-IP422 and TV-IP422W with the TV-H400. The IR light will cause reflection.

If you still encounter problems or have any questions regarding the **TV-H400**, please contact TRENDnet's Technical Support department.

Limited Warranty

TRENDnet warrants its products against defects in material and workmanship, under normal use and service, for the following lengths of time from the date of purchase.

TV-H400 - 2 Years Limited Warranty AC/DC Power Adapter, Cooling Fan and Power Supply carry a 1 year limited warranty

If a product does not operate as warranted during the applicable warranty period, TRENDnet shall reserve the right, at its expense, to repair or replace the defective product or part and deliver an equivalent product or part to the customer. The repair/replacement unit's warranty continues from the original date of purchase. All products that are replaced become the property of TRENDnet. Replacement products may be new or reconditioned. TRENDnet does not issue refunds or credit. Please contact the point-of-purchase for their return policies.

TRENDnet shall not be responsible for any software, firmware, information, or memory data of customer contained in, stored on, or integrated with any products returned to TRENDnet pursuant to any warranty.

There are no user serviceable parts inside the product. Do not remove or attempt to service the product by any unauthorized service center. This warranty is voided if (i) the product has been modified or repaired by any unauthorized service center, (ii) the product was subject to accident, abuse, or improper use (iii) the product was subject to conditions more severe than those specified in the manual.

Warranty service may be obtained by contacting TRENDnet within the applicable warranty period and providing a copy of the dated proof of the purchase. Upon proper submission of required documentation a Return Material Authorization (RMA) number will be issued. An RMA number is required in order to initiate warranty service support for all TRENDnet products. Products that are sent to TRENDnet for RMA service must have the RMA number marked on the outside of return packages and sent to TRENDnet prepaid, insured and packaged appropriately for safe shipment. Customers shipping from outside of the USA and Canada are responsible for return shipping fees. Customers shipping from outside of the USA are responsible for custom charges, including but not limited to, duty, tax, and other fees.

WARRANTIES EXCLUSIVE: IF THE TRENDNET PRODUCT DOES NOT OPERATE AS WARRANTED ABOVE, THE CUSTOMER'S SOLE REMEDY SHALL BE, AT TRENDNET'S OPTION, REPAIR OR REPLACE. THE FOREGOING WARRANTIES AND REMEDIES ARE EXCLUSIVE AND ARE IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, EITHER IN FACT OR BY OPERATION OF LAW, STATUTORY OR OTHERWISE, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. TRENDNET NEITHER ASSUMES NOR AUTHORIZES ANY OTHER PERSON TO ASSUME FOR IT ANY OTHER LIABILITY IN CONNECTION WITH THE SALE, INSTALLATION MAINTENANCE OR USE OF TRENDNET'S PRODUCTS.

TRENDNET SHALL NOT BE LIABLE UNDER THIS WARRANTY IF ITS TESTING AND EXAMINATION DISCLOSE THAT THE ALLEGED DEFECT IN THE PRODUCT DOES NOT EXIST OR WAS CAUSED BY CUSTOMER'S OR ANY THIRD PERSON'S MISUSE, NEGLIGENCE, IMPROPER INSTALLATION OR TESTING, UNAUTHORIZED ATTEMPTS TO REPAIR OR MODIFY, OR ANY OTHER CAUSE BEYOND THE RANGE OF THE INTENDED USE, OR BY ACCIDENT, FIRE, LIGHTNING, OR OTHER HAZARD.

LIMITATION OF LIABILITY: TO THE FULL EXTENT ALLOWED BY LAW TRENDNET ALSO EXCLUDES FOR ITSELF AND ITS SUPPLIERS ANY LIABILITY, WHETHER BASED IN CONTRACT OR TORT (INCLUDING NEGLIGENCE), FOR INCIDENTAL, CONSEQUENTIAL, INDIRECT, SPECIAL, OR PUNITIVE DAMAGES OF ANY KIND, OR FOR LOSS OF REVENUE OR PROFITS, LOSS OF BUSINESS, LOSS OF INFORMATION OR DATE, OR OTHER FINANCIAL LOSS ARISING OUT OF OR IN CONNECTION WITH THE SALE, INSTALLATION, MAINTENANCE, USE, PERFORMANCE, FAILURE, OR INTERRUPTION OF THE POSSIBILITY OF SUCH DAMAGES, AND LIMITS ITS LIABILITY TO REPAIR, REPLACEMENT, OR REFUND OF THE PURCHASE PRICE PAID, AT TRENDNET'S OPTION. THIS DISCLAIMER OF LIABILITY FOR DAMAGES WILL NOT BE AFFECTED IF ANY REMEDY PROVIDED HEREIN SHALL FAIL OF ITS ESSENTIAL PURPOSE.

Governing Law: This Limited Warranty shall be governed by the laws of the state of California.

Some TRENDnet products include software code written by third party developers. These codes are subject to the GNU General Public License ("GPL") or GNU Lesser General Public License ("LGPL").

Go to <http://www.trendnet.com/gpl> or <http://www.trendnet.com> Download section and look for the desired TRENDnet product to access to the GPL Code or LGPL Code. These codes are distributed WITHOUT WARRANTY and are subject to the copyrights of the developers. TRENDnet does not provide technical support for these codes. Please go to <http://www.gnu.org/licenses/gpl.txt> or <http://www.gnu.org/licenses/lgpl.txt> for specific terms of each license.

PWP05202009v2

Certifications

This equipment has been tested and found to comply with FCC and CE Rules.

Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received. Including interference that may cause undesired operation.



Waste electrical and electronic products must not be disposed of with household waste. Please recycle where facilities exist. Check with you Local Authority or Retailer for recycling advice.



NOTE: THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

ADVERTENCIA

En todos nuestros equipos se mencionan claramente las características del adaptador de alimentación necesario para su funcionamiento. El uso de un adaptador distinto al mencionado puede producir daños físicos y/o daños al equipo conectado. El adaptador de alimentación debe operar con voltaje y frecuencia de la energía eléctrica domiciliar existente en el país o zona de instalación.



Product Warranty Registration

Please take a moment to register your product online.
Go to TRENDnet's website at <http://www.trendnet.com/register>