




Guide d'installation rapide 

TK-EX3
1.01

Table of Contents

Français	1
1. Avant de commencer	1
2. Installation du matériel	2
.....	
Technical Specifications	6
Troubleshooting	7



Contenu de l'emballage

- 1 émetteur (périphérique local)
- 1 récepteur (périphérique distant)
- Guide d'installation rapide en plusieurs langues
- Adaptateur secteur (9V DC, 1A)
- Câble VGA combiné (1.2m / 4ft.)
- USB Type A à un câble de type B

Configuration du système

- Clavier PS/2
- Souris PS/2
- Moniteur compatible VGA
- Câble Ethernet Cat.5/5e/6
- USB Type A à un câble de type B (optional)
- Windows 7(32/64-bit)/Vista(32/64-bit)/XP(32/64-bit)/2000/2003 Server/Me/98SE

2. Procéder à l'installation

1. ETEIGNEZ correctement votre ordinateur et vos moniteurs.



2. Branchez le clavier PS/2 et la souris PS/2 au récepteur TK-EX3 (périphérique distant).



3. Branchez le moniteur au récepteur TK-EX3 (périphérique distant).



ENGLISH

FRANÇAIS

DEUTSCH

ESPAÑOL

РУССКИЙ

Connexion à l'ordinateur USB

4. Utilisez le câble VGA combiné pour brancher votre PC à l'extension KVM.



Vers l'émetteur TK-EX3
(périphérique local)



Vers PC

5. Branchez l'extrémité USB de type A du câble USB fourni à votre ordinateur.



Al transmissor TK-EX3
(dispositif local)

6. Branchez l'extrémité USB de type B du câble USB fourni au port USB de l'émetteur TK-EX3 (périphérique local).



7. Passez à l'étape 9.

Connexion à l'ordinateur PS/2

8. Utilisez le câble VGA combiné pour brancher votre ordinateur à l'émetteur TK-EX3 (périphérique local).

Vers l'émetteur TK-EX3 (périphérique local)



Vers PC

Vers le port clavier

Vers le port souris

Vers le port VGA



9. Branchez un câble Ethernet Cat.5/5e/6 entre le port Ethernet de l'émetteur (périphérique local) et le port Ethernet du récepteur (périphérique distant).



10. Branchez l'adaptateur secteur fourni au récepteur (périphérique distant) et à une prise de courant.



11. ALLUMEZ votre ordinateur et tous les moniteurs connectés



L'installation est maintenant complète.

Enregistrez votre produit

Afin d'être sûr de recevoir le meilleur niveau de service clientèle et le meilleur support possible, veuillez prendre le temps d'enregistrer votre produit en ligne sur:

www.trendnet.com/register

Nous vous remercions d'avoir choisi Trendnet

Technical Specifications

Connections	Connect to a computer or KVM switch
Connectors	Transmitter (local device): HDB 15-pin VGA USB type B RJ-45 port Receiver (remote device): HDB 15-pin VGA Mini din female RJ-45 port Power connector
Cables (included)	1 x VGA cable (VGA to VGA and PS/2), 1.2 m / 4 ft. 1 x USB cable (type A to type B), 1.2 m / 4 ft.
Supported OS	Windows 7/Vista/XP/2000, Linux
Resolution	Up to 100 m (328 ft.) with 1600 x 1200 resolution Up to 150 m (490 ft.) with 1280 x 1024 resolution
Power	9V DC, 1A
LEDs	Power, Link
Dimensions (L x W x H)	130 x 65 x 25 mm (5 x 2.6 x 1 in.)
Weight	Transmitter (local device): 275 g (9.7 oz.) Receiver (remote device): 290 g (10 oz.)
Temperature	Operating: 0° ~ 40° C (32° ~ 104° F) Storage: -20° ~ 60° C (-4° ~ 140° F)
Humidity	Max. 90% (Non-Condensing)
Certifications	CE, FCC

1. Do I need to use the included external AC adapter?

You must use the included external AC adapter with the TK-EX3 KVM switch.

2. I have the TK-EX3 connected properly, but my keyboard and mouse don't work. What should I do?

1. Make sure the power adapter is plugged into your TK-EX3 switch.
2. Verify that your mouse and keyboard are working properly by connecting them directly to the PS/2 ports on your computer.
3. Try using another set of PS/2 keyboard and mouse.

3. There is video distortion when I connect the monitor to the TK-EX3 receiver (remote device). What should I do?

1. You can adjust the quality of the video by adjusting the Gain (Resolution adjustment) and Equalization (contrast correction) knobs on the TK-EX3 receiver (remote device).
2. If you are using a cable longer than 100 meters, you will need to lower your computer's resolution to 1280 x 1024. The follow is the maximum length of cable supported by the TK-EX3:

Up to 100 m (328 ft.) with 1600 x 1200 resolution

Up to 150 m (490 ft.) with 1280 x 1024 resolution

If you still encounter problems or have any questions regarding the **TK-EX3**, please contact TRENDnet's Technical Support Department.

Limited Warranty

TRENDnet warrants its products against defects in material and workmanship, under normal use and service, for the following lengths of time from the date of purchase.

TK-EX3 - 2 Year Limited Warranty AC/DC Power Adapter, Cooling Fan and Power Supply carry a 1 year limited warranty

If a product does not operate as warranted during the applicable warranty period, TRENDnet shall reserve the right, at its expense, to repair or replace the defective product or part and deliver an equivalent product or part to the customer. The repair/replacement unit's warranty continues from the original date of purchase. All products that are replaced become the property of TRENDnet. Replacement products may be new or reconditioned. TRENDnet does not issue refunds or credit. Please contact the point-of-purchase for their return policies.

TRENDnet shall not be responsible for any software, firmware, information, or memory data of customer contained in, stored on, or integrated with any products returned to TRENDnet pursuant to any warranty.

There are no user serviceable parts inside the product. Do not remove or attempt to service the product by any unauthorized service center. This warranty is voided if (i) the product has been modified or repaired by any unauthorized service center, (ii) the product was subject to accident, abuse, or improper use (iii) the product was subject to conditions more severe than those specified in the manual.

Warranty service may be obtained by contacting TRENDnet within the applicable warranty period and providing a copy of the dated proof of the purchase. Upon proper submission of required documentation a Return Material Authorization (RMA) number will be issued. An RMA number is required in order to initiate warranty service support for all TRENDnet products. Products that are sent to TRENDnet for RMA service must have the RMA number marked on the outside of return packages and sent to TRENDnet prepaid, insured and packaged appropriately for safe shipment. Customers shipping from outside of the USA and Canada are responsible for return shipping fees. Customers shipping from outside of the USA are responsible for custom charges, including but not limited to, duty, tax, and other fees.

WARRANTIES EXCLUSIVE: IF THE TRENDNET PRODUCT DOES NOT OPERATE AS WARRANTED ABOVE, THE CUSTOMER'S SOLE REMEDY SHALL BE, AT TRENDNET'S OPTION, REPAIR OR REPLACE. THE FOREGOING WARRANTIES AND REMEDIES ARE EXCLUSIVE AND ARE IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, EITHER IN FACT OR BY OPERATION OF LAW, STATUTORY OR OTHERWISE, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. TRENDNET NEITHER ASSUMES NOR AUTHORIZES ANY OTHER PERSON TO ASSUME FOR IT ANY OTHER LIABILITY IN CONNECTION WITH THE SALE, INSTALLATION MAINTENANCE OR USE OF TRENDNET'S PRODUCTS.

TRENDNET SHALL NOT BE LIABLE UNDER THIS WARRANTY IF ITS TESTING AND EXAMINATION DISCLOSE THAT THE ALLEGED DEFECT IN THE PRODUCT DOES NOT EXIST OR WAS CAUSED BY CUSTOMER'S OR ANY THIRD PERSON'S MISUSE, NEGLIGENCE, IMPROPER INSTALLATION OR TESTING, UNAUTHORIZED ATTEMPTS TO REPAIR OR MODIFY, OR ANY OTHER CAUSE BEYOND THE RANGE OF THE INTENDED USE, OR BY ACCIDENT, FIRE, LIGHTNING, OR OTHER HAZARD.

LIMITATION OF LIABILITY: TO THE FULL EXTENT ALLOWED BY LAW TRENDNET ALSO EXCLUDES FOR ITSELF AND ITS SUPPLIERS ANY LIABILITY, WHETHER BASED IN CONTRACT OR TORT (INCLUDING NEGLIGENCE), FOR INCIDENTAL, CONSEQUENTIAL, INDIRECT, SPECIAL, OR PUNITIVE DAMAGES OF ANY KIND, OR FOR LOSS OF REVENUE OR PROFITS, LOSS OF BUSINESS, LOSS OF INFORMATION OR DATE, OR OTHER FINANCIAL LOSS ARISING OUT OF OR IN CONNECTION WITH THE SALE, INSTALLATION, MAINTENANCE, USE, PERFORMANCE, FAILURE, OR INTERRUPTION OF THE POSSIBILITY OF SUCH DAMAGES, AND LIMITS ITS LIABILITY TO REPAIR, REPLACEMENT, OR REFUND OF THE PURCHASE PRICE PAID, AT TRENDNET'S OPTION. THIS DISCLAIMER OF LIABILITY FOR DAMAGES WILL NOT BE AFFECTED IF ANY REMEDY PROVIDED HEREIN SHALL FAIL OF ITS ESSENTIAL PURPOSE.

Governing Law: This Limited Warranty shall be governed by the laws of the state of California.

Some TRENDnet products include software code written by third party developers. These codes are subject to the GNU General Public License ("GPL") or GNU Lesser General Public License ("LGPL").

Go to <http://www.trendnet.com/gpl> or <http://www.trendnet.com> Download section and look for the desired TRENDnet product to access to the GPL Code or LGPL Code. These codes are distributed WITHOUT WARRANTY and are subject to the copyrights of the developers. TRENDnet does not provide technical support for these codes. Please go to <http://www.gnu.org/licenses/gpl.txt> or <http://www.gnu.org/licenses/lgpl.txt> for specific terms of each license.

PWP05202009v2

Certifications

This equipment has been tested and found to comply with FCC and CE Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received. Including interference that may cause undesired operation.



Waste electrical and electronic products must not be disposed of with household waste. Please recycle where facilities exist. Check with you Local Authority or Retailer for recycling advice.



NOTE: THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

ADVERTENCIA

En todos nuestros equipos se mencionan claramente las características del adaptador de alimentación necesario para su funcionamiento. El uso de un adaptador distinto al mencionado puede producir daños físicos y/o daños al equipo conectado. El adaptador de alimentación debe operar con voltaje y frecuencia de la energía eléctrica domiciliar existente en el país o zona de instalación.



Product Warranty Registration

Please take a moment to register your product online.
Go to TRENDnet's website at <http://www.trendnet.com/register>