



## 1-Port Parallel Print Server

### TE100-P1P (v3.0R)

The 10/100 Mbps Parallel Print Server is designed to transform virtually any stand-alone parallel port printer into a shared network printer. Compact in design, but packed with features the TE100-P1P is the most cost effective way to add a parallel printer anywhere on your network!

## PRODUCT OVERVIEW

- Turns a standalone parallel printer into a shared network resource
- Manages print server through web browser or utility

## FEATURES

- Compliant with Bi-Directional 36-pin parallel port
- One 10/100 Mbps Auto-MDIX Fast Ethernet port
- Supports LPR printing for Windows
- Supports IPP printing for Windows 7, Vista, XP, 2000
- Web-based (HTTP) configuration
- Supports second HTTP port for remote Web configuration
- Supports Macintosh Rendezvous Zero Configuration\*
- Windows-based setup wizard and configuration utility
- Built-in flash memory for easy firmware upgrade
- 3-years limited warranty

\* Mac systems are only compatible with Post-Script printers

# 1-Port Parallel Print Server

TE100-P1P (v3.0R)

PRINT  
SERVER

## SPECIFICATIONS

### HARDWARE

<b>Standards</b>	<ul style="list-style-type: none"><li>• IEEE 802.3 10Base-T</li><li>• IEEE 802.3u 100Base-TX</li></ul>
<b>Printer Interface</b>	<ul style="list-style-type: none"><li>• IEEE 1284 Male Centronics (DB-36)</li></ul>
<b>LAN</b>	<ul style="list-style-type: none"><li>• 10/100 Mbps Auto-MDIX Ethernet port</li></ul>
<b>LEDs</b>	<ul style="list-style-type: none"><li>• Power, LPT, Link /Act</li></ul>
<b>Transport Protocol</b>	<ul style="list-style-type: none"><li>• TCP/IP, SMB</li></ul>
<b>Supported TCP/IP Protocol</b>	<ul style="list-style-type: none"><li>• DHCP, IPP, LPR, HTTP</li></ul>
<b>Supported OS</b>	<ul style="list-style-type: none"><li>• Windows 7 (32/64-bit), Vista (32/64-bit), 2003 Server, XP (32/64-bit), 2000, ME, 98SE</li><li>• Netware 5.x NDPS LPR Remote Printing (TCP/IP)</li><li>• Unixware, Linux</li><li>• Mac OS X 10.1~10.6</li></ul>
<b>Management</b>	<ul style="list-style-type: none"><li>• PS utility or web-browser configuration</li></ul>
<b>Power</b>	<ul style="list-style-type: none"><li>• 5V DC 2.5A external power adapter</li></ul>
<b>Dimensions</b>	<ul style="list-style-type: none"><li>• 57 x 90 x 32 mm (2.2 x 3.5 x 1.3 in.)</li></ul>
<b>Weight</b>	<ul style="list-style-type: none"><li>• 74 g (2.6 oz.)</li></ul>
<b>Temperature</b>	<ul style="list-style-type: none"><li>• Operating: 5°C~40°C (41°F~104°F)</li><li>• Storage: -25°C~50°C (-13°F ~122°F)</li></ul>
<b>Humidity</b>	<ul style="list-style-type: none"><li>• Max 95% (non-condensing)</li></ul>
<b>Certifications</b>	<ul style="list-style-type: none"><li>• CE, FCC</li></ul>

## NETWORKING SOLUTIONS

### 1-Port Parallel Print Server (TE100-P1P)



Modem/  
Router



Parallel Printer

## PACKAGE CONTENTS

TE100-P1P

Multi-Language Quick Installation Guide

CD-ROM (Utility & User's Guide)

Power Adapter (5V DC, 2.5A)

## RELATED PRODUCTS

TEW-MFP1	1-Port Wireless N Multi-Function USB Print Server
TE100-P21	3-Port Print Server
TW100-S4W1CA	4-Port Broadband Router

## CONTACT INFORMATION

**TRENDnet**

20675 Manhattan Place, Torrance, CA 90501 USA

Tel: 1-310-961-5500

Fax: 1-310-961-5511

Web: [www.trendnet.com](http://www.trendnet.com)

Email: [sales@trendnet.com](mailto:sales@trendnet.com)

**1-888-326-6061**

