

**150Mbps Wireless N PCI Adapter
(TEW-703PI)**

**150Mbps Low Profile Wireless N PCI Adapter
(TEW-703PIL)**

- Quick Installation Guide [1]

1. Before You Start

Package Contents

- TEW-703PI/TEW-703PIL
- CD-ROM (Utility and User's Guide)
- Multi-Language Quick Installation Guide
- 1 detachable antenna

Minimum Requirements


- 32-bit PCI 2.2 slot
- CD-ROM Drive

Supported Operating Systems	CPU	Memory
Windows 7 (32/64-bit)	1GHz or above	1GB RAM or above
Windows Vista (32/64-bit)	800MHz or above	512MB RAM or above
Windows XP (32/64-bit)	300MHz or above	256MB RAM or above


2. How to Install

Important! DO NOT install the TEW-703PI/TEW-703PIL in the computer until instructed to do so.

1. Insert the **Utility & Driver CD-ROM** into your computer's CD-ROM Drive.
2. Click **Run Autorun.exe** (Windows 7/Vista only).
3. Click **Install Utility & Driver**.




4. Follow the **InstallShield Wizard** instructions.
Then click **Finish**.



5. Shutdown your computer.
6. Open your computer's case.
7. Insert PCI Card firmly into an available PCI Card slot of desktop PC, attach the included antenna, and then turn ON the computer and wait until the Windows desktop appears.

Note: Windows 7/Vista will automatically detect and install the appropriate drivers. For Windows XP, proceed to 8.

8. Follow the Found New Hardware Wizard instructions. Then click **Finish**.



Your installation is now complete


3. Connect to a Wireless Network

1. On the bottom right-hand corner of the screen, double-click on the **Wireless Configuration Utility** icon. On Windows 7, if the icon does not appear, click the Show hidden icons arrow.




2. Click **Available Networks**.

3. Select a SSID and then click **Add Profile**. The SSID is the wireless network name of your wireless network (e.g. wireless router or access point).



4. If Encryption is enabled on your wireless network (e.g. access point or wireless router), the correct Network Authentication and Data Encryption type should be selected. Enter the Network Key (wireless network password), confirm the network key and then click **OK**.



You are now connected to a wireless network

For detailed information regarding the **TEW-703PI/TEW-703PIL** configuration and advanced settings, please refer to the User's Guide included on the Utility & Driver CD-ROM or TRENDnet's website at www.trendnet.com.

Declaration of Conformity



Company Information:

Company Name:

TRENDnet, Inc.

Company Address:

20675 Manhattan Place

Torrance, CA 90501

USA

Product Information:

Product Description:

150Mbps Wireless N PCI Adapter

150Mbps Low Profile Wireless N PCI Adapter



Model Number:

TEW-703PI

TEW-703PIL

Brand name:

TRENDnet

Technical Standards:

EN 300 328 V1.7.1: 10-2006

EN 301 489-1 V1.8.1: 04-2008

EN 301 489-17 V2.1.1: 05-2009

EN 62311 : 2008

EN 60950-1: 2006 + A11 : 2009 + A1 : 2010

Declaration:

The product is herewith confirmed to comply with the requirements of Directive 1999/5/EC of the Council (European Parliament) on the radio and telecommunications terminal equipment.

I hereby declare that the products and devices mentioned above are consistent with the standards and provisions of the guidelines.

Sonny Su

Full Name

August 19, 2011

Date

Director of Technology

Position / Title

Signature



Product Warranty Registration

Please take a moment to register your product online.
Go to TRENDnet's website at <http://www.trendnet.com/register>

Certifications

This equipment has been tested and found to comply with FCC and CE Rules.
Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received. Including interference that may cause undesired operation.



Waste electrical and electronic products must not be disposed of with household waste. Please recycle where facilities exist. Check with you Local Authority or Retailer for recycling advice.



NOTE: THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

ADVERTENCIA

En todos nuestros equipos se mencionan claramente las características del adaptador de alimentación necesario para su funcionamiento. El uso de un adaptador distinto al mencionado puede producir daños físicos y/o daños al equipo conectado. El adaptador de alimentación debe operar con voltaje y frecuencia de la energía eléctrica domiciliar existente en el país o zona de instalación.

TRENDnet
20675 Manhattan Place
Torrance, CA 90501. USA