



Руководство по быстрой установк 

TFM-560X
YO.13

Table of Contents

Русский	1
1. Что нужно сделать в самом начале	1
2. Порядок установки	2
Troubleshooting	6

1. Что нужно сделать в самом начале



Содержимое упаковки

- TFM-560X
- CD-ROM (служ. программа и драйверы)
- Руководство по быстрой установке на нескольких языках
- Телефонный кабель RJ11
- Последовательный кабель RS-232
- AC Адаптер источника питания (9V AC, 1A)

Требования к установке

- Дискковод CD-ROM
- RS-232 COM-порт
- Место на накопителе на жестких дисках: 4Мб или более

Поддерживаемые OS	ЦП	Память
Windows 7 (32/64-bit)	1ГГц или выше	1GB RAM или более
Windows Vista (32/64-bit)	800МГц или выше	512МБ RAM или более
Windows XP (32/64-bit) / 2000 / ME / 98SE	300МГц или выше	256МБ RAM или более

2. Порядок установки

Примечание:

См. руководство пользователя на компакт-диске с драйверами, где приведены указания по установке в Windows 98SE и Windows ME.



1. Вставка **Driver CD-ROM** в привод CD-ROM вашего компьютера.

2. Щелкните по кнопке **Run Autorun.exe** (только Windows 7/Vista).

3. Нажмите «**Установить драйвер**» (Install Driver) и затем выберите **Вашу** операционную систему.

4. Щелкните по кнопке **OK**.

5. Нажмите **Exit** (Завершить), чтобы закрыть окно установки.



6. Отключите компьютер.

7. Вставьте штыревой конец кабеля RS-232 в гнездо устройства TFM-560X. Затем подключите гнездовую контакт-деталь кабеля RS-232 к COM-порт своего компьютера.



8. Присоедините один конец телефонного провода RJ-11 к гнезду Line модема, а другой конец к телефонному гнезду.

9. Подключите силовой адаптер к модему и сетевой розетке.

10. Включите модем.

11. Включите модем. Подключите телефон к гнезду телефона **Phone** (дополнительное).

12. Включите PC.



Примечание:

На Windows 7/2000 драйверы установятся автоматически. Установка драйвера под 7/2000 завершена. В Windows Vista перейдите к шагу 13. В Windows XP перейдите к шагу.

Windows Vista

13. Щелкните по кнопке **Locate and install driver software** (рекомендуется).



14. Нажмите **Install this driver software anyway** (Все равно установить драйвер).




Примечание: Установка драйвера под Vista завершена.

Windows XP

15. Выберите **Нет** и щелкните по кнопке **Далее** (Next).



16. Выберите **Установить программное обеспечение автоматически** (Install the software automatically) и щелкните по кнопке **Далее** (Next).



17. Выберите Windows XP драйверы, а затем нажмите кнопку **Далее**.



18. Щелкните по кнопке **Все равно продолжить** (Continue Anyway).



19. Щелкните по кнопке **Завершить**.



Примечание: Установка драйвера под XP завершена.

1. I inserted the Driver CD-ROM into my computer's CD-ROM Drive but the installation menu does not appear automatically. What should I do?

1. For Windows 7, if the installation menu does not appear automatically, click on the Windows Icon on the bottom left hand corner of the screen., click the "Search programs and files" box, and type D:\Autorun.exe, where "D" in "D:\Autorun.exe" is the letter assigned to your CD-ROM Drive, and then press the ENTER key on your keyboard.
2. For Windows Vista, if the installation menu does not appear automatically, click Start, click the Start Search box, and type D:\Autorun.exe where "D" in "D:\Autorun.exe" is the letter assigned to your CD-ROM Drive, and then press the ENTER key on your keyboard.
3. For Windows XP/2000, if the window does not appear automatically, click Start, click Run and type D:\Autorun.exe where "D" in "D:\Autorun.exe" is the letter assigned to your CD-ROM Drive, and then press the ENTER key on your keyboard.

2. I connected the modem to my computer's COM/RS-232 port and my computer does not detect the modem? What should I do?

1. Make sure the computer meets the minimum system requirements as shown at the beginning of this quick installation guide.
2. Verify that the modem is properly connected to the computer's RS-232 port.
3. Try connecting the modem into a different RS-232 port.

3. After successful installation of the TFM-560X, I tried to connect to the Internet but I do not get a dial tone. What should I do?

1. Unplug the telephone wire from the computer, and check for a dial tone by connecting the telephone cable directly from the wall outlet to a telephone. If there is no dial tone, then the problem is in your telephone cable or telephone system. Call your telephone service provider for assistance. If there is a dial tone, reconnect cables to the modem and verify that the telephone cable is securely connected to the modem and phone jack.
2. Make sure you are connecting the modem into an analog phone connection. The modem will not work with a digital phone line.
3. Contact your ISP and verify all the information that you have in regards to your Internet connection settings is correct.

4. How do I install the drivers on Windows 98SE or ME?

Please refer to the User's Guide included on the Driver CD-ROM.

5. Do I need to install the Modem on Hold or Classic Phone Tools software programs?

The Modem on Hold or Classic Phone Tools software programs are not required to operate the modem. To use Modem on Hold or Classic Phone Tools, open the program and click on the Help button.

If you still encounter problems or have any questions regarding the **TFM-560X** please contact TRENDnet's Technical Support Department.

Certifications

This equipment has been tested and found to comply with FCC and CE Rules.

Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received. Including interference that may cause undesired operation.



(01)07898431241061

0001-06-2375

Este equipamento opera em caráter secundário, isto é, não tem direito a proteção contra interferência prejudicial, mesmo de estações do mesmo tipo, e não pode causar interferência a sistemas operando em caráter primário



Waste electrical and electronic products must not be disposed of with household waste. Please recycle where facilities exist. Check with you Local Authority or Retailer for recycling advice.



NOTE: THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

ADVERTENCIA

En todos nuestros equipos se mencionan claramente las características del adaptador de alimentación necesario para su funcionamiento. El uso de un adaptador distinto al mencionado puede producir daños físicos y/o daños al equipo conectado. El adaptador de alimentación debe operar con voltaje y frecuencia de la energía eléctrica domiciliar existente en el país o zona de instalación.



Product Warranty Registration

Please take a moment to register your product online.
Go to TRENDnet's website at <http://www.trendnet.com/register>