

TK-204UK General Quick Reference Sheet				
Command	Hot Keys	Front Panel Button	Description	
Select computer	Scroll Lock + Scroll Lock + (x) (x) = 1~2 for PC channel	Press any push button	Select the desired computer	
Next computer port	Scroll Lock + Scroll Lock + or Scroll Lock + Scroll Lock + or Scroll Lock + Scroll Lock + Backspace	Press Push Button for a specific port on the switch	Select the next computer port	
Autoscan	Scroll Lock + Scroll Lock + S	_	Autoscan through every connected channel for quick screen browsing of each channel (scan delay = 10 seconds)	
Autoscan with Programmable Delay Time	Scroll Lock + Scroll Lock + S + (x)	-	Autoscan through every connected channel for quick screen browsing of each channel (10-100 seconds)	
Stop Autoscan	Press any key on keyboard	Press any push button or key	Terminate Autoscan activity	
Beep Sound On/Off	Scroll Lock + Scroll Lock + B	_	Toggle On/Off beep sound	
Define Hotkey Sequence (default = Scroll Lock + Scroll Lock)	Scroll Lock + Scroll Lock + H + (Y) Y = Scroll Lock, Caps Lock, Esc, F12 or Num Lock	Press and hold down button 4 until you hear 2 beeps, then release the button and press (Y) You should hear 1 beep after you press (Y) (Y) = Scroll Lock, Caps Lock, Esc, F12 or Num Lock	Select the hotkey preceding sequence among 5 options	



Speaker/Microphone/USB Port Quick Reference Sheet				
Command	Hot Keys	Front Panel Button	Description	
Select Audio / Microphone	Scroll Lock + Scroll Lock + (Fx)	_	Select the desired Audio / Microphone channel	
Bind Computer & Audio/Microphone Switching	Scroll Lock + Scroll Lock Q	_	Bind Audio/Microphone to computer port switching. (Default Setting)	
UnBind Computer & Audio / Microphone Switching	Scroll Lock + Scroll Lock + W	_	Unbind Audio/Microphone to computer port switching	
Select USB Port	Scroll Lock + Scroll Lock + (Fy)	_	Select the desired USB port	
Bind Computer and USB Port Switching	Scroll Lock + Scroll Lock + Z	Press any push button or key	Bind USB port to computer port switching. (Default Setting)	
Unbind Computer and USB Port Switching	Scroll Lock + Scroll Lock + X	_	Unbind USB port to computer port switching	

Note: The hotkey sequence Scroll Lock + Scroll Lock + (Key) denotes that you should hit the individual key

consecutively one at a time, not simultaneously.