


## Installation Procedures:

1. Remove the TEW-222CF from the PDA's CompactFlash slot.
2. Backup important files on your PDA or do a complete backup. Save the backup file on a memory disk or save it on the computer. **We are not responsible for the loss data in your PDA.**

**Note: you could also perform a hard-reset on the PDA to erase all data and restore the settings back to the factory default. If this is the case, you can go to step 3 and then go through step 13 ~ 18 to install the new driver.**

3. Connect the PDA to a host computer that is running the "Microsoft ActiveSync" (we used version 3.7 in this procedure) and Synchronize the PDA to the computer (sync with Guest Partnership connection is ok).
4. On the computer, go to "Start", "Settings", click on "Control Panel".
5. Double click on "Add or Remove Programs", find the "PRISM WIRELESS FOR CE...", click on it to highlight, click on "Remove/Change" button, and click "Yes" to remove the program.




6. On the PDA, tap on "start", tap on "settings", tap on "system" at the bottom, and tap on "remove programs" icon.
7. Tap to highlight the "Wireless PRISM Wireless LAN for Win...", tap "Remove" at the bottom, and tap "Yes". Wait a few seconds for the PDA to remove the program.
8. On the computer, open the "Microsoft ActiveSync" and click on "Explore".



9. Double-click on “My Pocket PC”.



10. Double-click “Windows” folder.




11. Search and delete any file with file name that starts with “PRISM” (i.e. prismnds.dll). You should have found none.

12. From the computer, unzip the new TEW-222CF driver file that you have obtained from TRENDnet to the computer’s hard drive (i.e. C:\TEW222CF).

13. Double-click on the “PrismForPocketCE4.exe” file.


14. Click “Next”.




15. Click “Yes” and you should see the computer and PDA’s screen show installation progress.



16. Click “Ok”.



17. Click “Finish”.



18. Insert the TEW-222CF into the PDA’s CompactFlash slot and configure the wireless settings on the screen to connect to the wireless device.

19. End of the document.

If you need help performing the driver uninstall and reinstall, please call us at Tel: 310-891-1100 or send e-mail to [support@trendware.com](mailto:support@trendware.com).

Support Hours are Monday ~ Friday, 7:30AM ~ 6:00PM Pacific Standard Time (except holidays).